## ThinkCentre Tiny-in-One (TIO) 23

Model	10DQPAR6US					
Form factor	Tiny-in-One, offers a full All-In-One experience when optional Tiny slots into					
Compatible Tiny:	•	the back of TIO 23, clean cabling and effortless setup				
Compatible Tiny:	M93/p Tiny, M83 Tiny, M73 Tiny, or M53 Tiny * Processor, memory, storage, operating system, WLAN, Bluetooth,					
	Keyboard, mouse, etc., depend on the Tiny installed (optional)					
Panel Viewable image size	TFT-LCD, twisted nematic (TN), White LED backlight					
Max view area (W x H)	23.0" (584.2mm) diagonal 20.05" x 11.28" / 509.2mm x 286.4mm					
Optimum resolution Aspect ratio	<b>1920x1080</b> 16:9					
Pixel pitch (mm)	.265mm					
Dot/Pixel per Inch Brightness	96 dpi 250 nits or cd/m² (typical)					
Contrast ratio	1000:1 (typical)	, p. 100.1)				
Pixel response time Color gamut	5ms (typical) 72%					
Anti-reflective	Anti-glare					
Horizontal frequency Vertical frequency	30 to 83kHz 50 to 75Hz					
Viewing angle at 10:1 CR170° (+/- 85°) horizontal, 160° (+/- 80°) vertical						
Preset resolutions	640x350 @ 70Hz	66Hz 72Hz 75Hz				
	640x480 @ 60Hz, 66Hz, 72Hz, 75Hz 720x400 @ 70Hz					
	800x600 @ 60Hz, 72Hz, 75Hz 1024x768 @ 60Hz, 70Hz, 75Hz					
	1152x864 @75Hz					
	1280x800 @ 60Hz 1280x1024 @ 60H					
	1366x768 @ 60Hz					
	1440x900 @ 60Hz, 75Hz 1600x1200 @ 60Hz, 70Hz, 75Hz					
	1680x1050 @ 60Hz					
Presets / user settings	1920x1080 @ 60Hz Presets: 25; user settings: 25					
On screen display	On screen display with digital user controls (8 languages)					
Control features	Mode-switching (TIO mode / standalone monitor mode, switches video/ audio/USB input source) / Back button, Left shift button, Right shift / Bright-					
T: : 0 D 0	ness button, Selection button / Menu button, Power button					
Tiny-in-One Power On	Pressing Alt + P on keyboard or pressing Power button positioned on TIO can turn on both TIO and Tiny (only some Tiny support, see compatible list)					
USB ports	Front: two USB 3.0 (only when M93/p or M83 installed) or two USB 2.0					
	Side: two USB 2.0, one USB 2.0 upstream port (connect to PC), one mini USB 2.0 port for accessories (on top)					
	* The USB ports are only available when a Tiny is istalled or a PC is					
connected via USB upstream port Monitor connectors One DisplayPort port, version 1.2						
3-in-1 Cable	Undetachable 3-in-1 cable (Power connecter, USB, DisplayPort), only for					
Audio port	connecting to Tiny installed (optional) one headphone / microphone combo jack (stereo, 3.5mm)					
Security	Security keyhole for attachment of optional cable lock (Kensington® lock					
		optional Tiny and ODD box fered by Tiny installed (op	x with TIO 23 together, more tional)			
Mechanical	Dimensions	TIO 23 without stand	TIO 23 with stand			
	W x D x H (inch)	22.17 x 2.74 x 14.88	22.17 x 9.84 x 16.15 - 20.48			
	W x D x H (mm)	563 x 69.5 x 378	563 x 250 x 410.14 - 520.14			
	Weight (approximately)	TIO 23 with stand	TIO 23 with Tiny, stand, and ODD box installed			
	lb / kg	15.4lb / 7kg	18.9lb / 8.58kg			

Mounting features  Adjustable stand	Wall or desk mounting using the extend arm or third-party accessories meeting the VESA FPMPMI® (100mm mount)  Tilt: 35° back, -5° forward; lift: 4.3" (110mm); swivel: +/-45°
Power supply Power consumption	90 watts AC/DC adapter, 88% PSU, universal 22 watts typical, 45 watts maximum, <0.5 watts standby / suspend
Limited warranty <sup>3</sup>	<b>3-years</b> , Customer Carry-In Exchange (CCE) via Rapid Replacemen, IWS (International Warranty Service <sup>9</sup> ) / service upgrades available For Lenovo service upgrade options, please go to S-TC sheet
VESA-compliant <sup>2</sup> Ergonomics Emission standards Environmental Windows certifications	VESA DDC2B/CI, VESA DPMS-compliant ISO 9241-307 FCC Class B TCO (TCO Certified Edge 1.1), WEEE, RoHS, ENERGY STAR® 6.0 EPEAT™ Gold rating, ULE, TUV Windows 7, Windows 8, and Windows 8.1 certified
Ship group	TIO 23 (Monitor), detachable stand, Information flyer, Reference and driver CD, AC/DC power adapter, power cord, quickly-released screw
Accessories	For compatible accessories, please go to TC-AQP sheet

ThinkCentre Tiny-in-One 23 Compatible list					
Model	M900 Tiny, M700 Tiny, M600 Tiny, M83 Tiny, M53 Tiny	M93/p Tiny, M73 Tiny	Chromebox		
Turn on TIO and Tiny together via Alt + P on USB KB	All models	All models	Not support		
Turn on TIO and Tiny together via TIO Power Button	All models	TIO models	All models		