

# **PERFORMANCE**

### **Processor**

### **Processor Family**

11th Generation Intel® Core™ i5 Processor

#### **Processor**

Processor Name	Cores	Threads	Base Frequency	Max Frequency	Cache	Memory Support	Processor Graphics
Core™ i5-1145G7E	4	8	1.5GHz	4.1GHz <sup>[1]</sup>	8MB	DDR4-3200	Intel® Iris® Xe Graphics

#### Notes:

[1] Intel® Max Turbo frequency will vary depending on application workload and the hardware and software configurations, see

http://www.intel.com/technology/turboboost/ for more information.

# **Operating System**

## Operating System\*\*

- Windows® 11 IoT Enterprise GAC 64
- Windows® 10 IoT Enterprise SAC 64

# **Graphics**

### **Graphics**

Graphics	Туре	Memory	Connector	Max Resolution
Intel® Iris® Xe Graphics	Integrated	Shared	2x HDMI®	3840x2160@24Hz(HDMI®)

# **Chipset**

# Chipset

Intel® SoC (System on Chip) platform

## **Memory**

## **Max Memory**

16GB soldered memory, not upgradable

### **Memory Slots**

Memory soldered to systemboard, no slots, dual-channel

### **Memory Type**

DDR4-3200

# **Storage**

### **Storage Support**

One drive, up to 256GB SSD

### **Storage Type**

Disk Type	Interface
M.2 2280 SSD	PCIe® NVMe®, PCIe® 3.0 x4
M.2 2242 SSD	PCIe® NVMe®, PCIe® 3.0 x4

# **Power Supply**

## **Power Supply**

Power	Туре	Efficiency	Key Features
90W	Adapter	89%	Autosensing

# **DESIGN**

# Mechanical



# Component Options\*\*

Product	Compute System	Controller	Audio Bar	Microphone Component	Camera Component
ThinkSmart™ Core™ Full Room Kit (ThinkSmart™ Controller)	1x ThinkSmart™ Core™	1x ThinkSmart™ Controller	1x ThinkSmart™ Bar	(Optional) 2x Satellite Microphone	1x ThinkSmart™ Cam
ThinkSmart™ Core™ Full Room Kit (ThinkSmart™ Controller + ThinkSmart™ Bar 180)	1x ThinkSmart™ Core™	1x ThinkSmart™ Controller	1x ThinkSmart™ Bar 180	-	-
ThinkSmart™ Core™ + ThinkSmart™ Controller	1x ThinkSmart™ Core™	1x ThinkSmart™ Controller	-	-	-
ThinkSmart™ Core™ Full Room Kit (Lenovo® IP Controller)	1x ThinkSmart™ Core™	1x Lenovo® IP Controller	1x ThinkSmart™ Bar	(Optional) 2x Satellite Microphone	1x ThinkSmart™ Cam
ThinkSmart™ Core™ Full Room Kit (Lenovo® IP Controller + ThinkSmart™ Bar 180)	1x ThinkSmart™ Core™	1x Lenovo® IP Controller	1x ThinkSmart™ Bar 180	-	-
ThinkSmart™ Core™ + Lenovo® IP Controller	1x ThinkSmart™ Core™	1x Lenovo® IP Controller	-	-	-
ThinkSmart™ Core™ Generic	1x ThinkSmart™ Core™	-	-	-	-

## Controller\*\*

Component Name	Display	Sensors	Multi- touch	Ports	Key Features
Lenovo® IP Controller	• 10.1" Display, HD (1280x800) • 360 nits brightness • 16:10 aspect ratio • Anti- Fingerprint	Human Presence Sensor	10- point touch	• 1x Gigabit Ethernet (RJ-45) • 1x Kensington® Security Slot™ • 1x HDMI®-in • 1x Power Connector (on Link Box) • 1x Gigabit Ethernet (RJ-45, on Link Box) • 1x HDMI® out (on Link Box) • 1x USB-B (on Link Box)	Wall mountable (For wall mounting, mount kits are needed. The kits are sold separately and coming soon)
ThinkSmart™ Controller	• 10.1" Display, HD (1280x800) • Up to 340 nits brightness • 16:10 aspect ratio • Anti- Fingerprint, Anti-Glare • 30° or 60° rotatable	IR sensors for motion detection, up to 3 meters distance and 90° angle	10- point touch	• 1x USB-C® (connect to compute unit, 10m USB-C® cable incluided) • 1x 3.5mm headphone / mic combo jack • 1x Kensington® MiniSaver Security Slot	-
No Controller	-	-	-	-	-

### Audio Bar\*\*

Component Name	Speaker	Microphone	Camera	Noise Control	Ports	Key Features
ThinkSmart™ Bar	· '	• 4x Forming mic array, with 180° coverage • 300 Hz to 8	-	cancellation	• 1x USB-C® (USB 2.0, connect to ThinkSmart™ Core™ compute unit)	• Bluetooth® 5.0 (A2DP, SBC, MPEG-4, AAC) • (Optional) Wall



	• Up to 97dB to cover large meeting room • 250 Hz to 20 KHz frequency range	KHz frequency range			• 1x AUX in (connect to Mic Pod)	and TV mounting
ThinkSmart™ Bar 180	4x Speaker (2x woofer, 2x tweeter)     Stereo audio out     80 Hz to 20 KHz frequency range	8x microphone beamforming array     -37dBFS sensitivity     100 Hz to 8 KHz frequency range	• 3x Camera • 13 megapixels • Up to 3840 x 1080@30fps • 180° Horizontal FoV, 54° Vertical FoV	Noise Cancellation support	• 1x USB-C® • 1x USB 3.2 Gen 1 • 1x RJ 45	• Integrated People Count • Automatic Speaker Detection • Intelligent Zoom • Bluetooth® connection for Remote Controller and app control • Wall mount kit
No Audio Bar	-	-	-	-	-	-

# Microphone Component\*\*

Component Name	Capturing Range	Ports
Satellite Microphone	1m 360 degree omni direction	<ul> <li>1x Mic out (connect to ThinkSmart™ Bar)</li> <li>1x Mic in (connect to next Mic Pod)</li> </ul>
No Microphone	-	-

# Camera Component\*\*

Component Name	Image	Optics	Ports	Key Features
ThinkSmart™ Cam	• Up to 4K at 30fps resolutions (USB 3.2 Gen 1 Cable)	• 100° Horizontal FoV • 68° Vertical FoV • 125° Diagonal FoV	1x USB-C® (connect to ThinkSmart™ Core™ compute unit)	Standalone (tabletop), (Optional) Wall and TV mounting Image output format:MPEG, H.264, YUV UVC (USB Video Class) 1.1 plug-and-play support Al conference meeting function: auto zoom, auto framing, people counting, speaker tracking, whiteboard awareness HDR (High Dynamic Range) support
No Camera	-	-	-	-

# Dimensions (WxDxH)[1]

Models	Dimensions
ThinkSmart™ Cam	105 x 60.5 x 36 mm (4.1 x 2.4 x 1.4 inches)
ThinkSmart™ Core™	226 x 200 x 37.5 mm (8.9 x 7.9 x 1.5 inches)
ThinkSmart™ controller	265.5 x 13 x 168.1 mm (10.5 x 0.5 x 6.6 inches)
ThinkSmart™ controller with stand	265.5 x 83.3 x 168.1 mm (10.5 x 3.3 x 6.6 inches)
ThinkSmart™ Bar 180	650 x 80 x 125 mm (25.6 x 3.1 x 4.9 inches)
ThinkSmart™ Bar	800 x 90 x 55 mm (31.5 x 3.5 x 2.2 inches)
Lenovo® IP controller	248 x 151 x 100 mm (9.76 x 5.94 x 3.94 inches)
Satellite Microphone	Diameter: 100 mm (3.9 inches)     Height: 20 mm (0.8 inches)

# Weight<sup>[2]</sup>

Models	Weight
ThinkSmart™ Bar 180	Around 2.2 kg (4.85 lb)

# ThinkSmart Core for Zoom



ThinkSmart™ Core™	1.1 kg (2.4 lbs)
Satellite Microphone	220 g (0.5 lbs)
ThinkSmart™ Cam	220 g (0.5 lbs)
ThinkSmart™ Bar	1.9 kg (4.2 lbs)
ThinkSmart™ controller	753.8 g (1.7 lbs)
Lenovo® IP controller	Around 0.97 kg (2.16 lbs)

#### **Case Color**

Black

Notes:

[1] The system dimensions may vary depending on configurations.

[2] The system weight is approximate and based on results in Lenovo® lab, which varies depending on the source of component, variance of the distribution of each component, and manufacturing process. It may not be the exact weight for each specific model.

### CONNECTIVITY

## **Network**

# Ethernet

Gigabit Ethernet, Intel® Ethernet Connection I219-LM, 1x RJ-45, supports Wake-on-LAN

#### WLAN + Bluetooth®\*\*

- Intel® Wireless-AC 9260, 802.11ac Dual Band 2x2 Wi-Fi® + Bluetooth® 5.0, Intel® vPro® technology support, M.2 card
- Intel® Wi-Fi® 6 AX201, 802.11ax 2x2 Wi-Fi® + Bluetooth® 5.0, Intel® vPro® technology support, M.2 Card

### Ports<sup>[1]</sup>

### Rear Ports[2]

- 1x Thunderbolt<sup>™</sup> 4
- 1x USB-C® 3.2 Gen 1
- 1x USB-C® 3.2 Gen 2
- 1x USB 3.2 Gen 1
- 2x USB 3.2 Gen 2
- 1x HDMI®-in
- 2x HDMI®-out 1.4
- 1x Ethernet (RJ-45)
- 1x power connector

#### Notes:

[1] The transfer speed of following ports will vary and, depending on many factors, such as the processing speed of the host device, file attributes and other factors related to system configuration and your operating environment, will be slower than theoretical speed.

USB 2.0: 480 Mbit/s;

USB 3.2 Gen 1 (SuperSpeed USB 5Gbps, formerly USB 3.0 / USB 3.1 Gen 1): 5 Gbit/s;

USB 3.2 Gen 2 (SuperSpeed USB 10Gbps, formerly USB 3.1 Gen 2): 10 Gbit/s;

USB4® 20Gbps / USB 3.2 Gen 2x2 (SuperSpeed USB 20Gbps): 20 Gbit/s;

USB4® 40Gbps (USB 40Gbps): 40 Gbit/s;

Thunderbolt™ 3/4: 40 Gbit/s.

[2] Ports on Compute System (ThinkSmart™ Core™) only. Components' ports refer to components' specifications.

## **SECURITY & PRIVACY**

### Security

### **Security Chip**

Discrete TPM 2.0, TCG certified

### **Physical Locks**

Kensington® Security Slot™



#### **BIOS Security**

- Power-on password
- Supervisor password
- Hard disk password
- Smart USB protection

## **MANAGEABILITY**

# **System Management**

**System Management** 

Intel® vPro® with Intel® AMT 15

### SERVICE

# **Warranty**<sup>[1]</sup>

#### **Base Warranty**

3-year limited onsite service

### Notes:

[1] The warranty upgrades may be bundled with some models, please check the "Included upgrade" column in the specific model's configurations. For more service extensions, please go to <a href="https://smartfind.lenovo.com/">https://smartfind.lenovo.com/</a>. To learn more details of warranty policy, please access <a href="https://pcsupport.lenovo.com/warranty">https://pcsupport.lenovo.com/warranty</a>.

## **SOFTWARE**

### **Preinstalled Software**

### **Preinstalled Software**

Zoom Rooms Application

- This is a telepresence technology product.
- Feature with \*\* means that only one offering listed under the feature is configured on selected models.
- Lenovo reserves the right to change specifications or other product information without notice. Lenovo is not
  responsible for photographic or typographical errors. LENOVO PROVIDES THIS PUBLICATION "AS IS,"
  WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING THE IMPLIED WARRANTIES
  OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some jurisdictions do not allow
  disclaimer of express or implied warranties in certain transactions, therefore this disclaimer may not apply to
  you.
- The specifications on this page may not be available in all regions, and may be changed or updated without notice.







intel





intel



